

CW501/8

5" LF Driver



MOUNTING INFORMATION

Overall Diameter	130 mm
Bolt Circle Diameter	138 mm
Baffle cutout Diameter	115 mm
Depth	56 mm
Mounting Depth	49 mm
Net Weight	0,6 Kg

SPECIFICATIONS

Nominal Impedance	8 Ohm
Power	40W
Sensitivity (1W/1m)	92 dB
Frequency Range	80-6000 Hz
Voice Coil Diameter	25 mm
Magnet	Ferrite
Magnet weight	10 oz
Basket Material	Steel

THIELE AND SMALL PARAMETERS

Qes	1,197
Qms	4,800
Qts	0,958
Vas	3,201 l
Sd	86,54 cm ²
Mms	7,839 g
Bl	3,918 Tm
Cms	301,006 μm/N